

# DIGITAL MULTIMETER

MODEL : DM321T



## 3½ Digits, True RMS, Manual Ranging

With Holster, Auto Power Off, Data Hold & Back Light, A/V Continuity Test, Capacitance Test, Tr. (hFE) Test

Parameter	Range
<b>DC Voltage</b>	200 mV, 2 V, 20 V, 200 V, 1000 V
<b>AC Voltage (True RMS)</b>	2 V, 20 V, 200 V, 750 V
<b>DC Current</b>	20 $\mu$ A, 2 mA, 20 mA, 200 mA, 20 A
<b>AC Current (True RMS)</b>	20 mA, 200 mA, 20 A
<b>Resistance</b>	200 $\Omega$ , 2 K $\Omega$ , 20 K $\Omega$ , 200 K $\Omega$ , 2 M $\Omega$ , 20 M $\Omega$
<b>Capacitance (Auto Ranging)</b>	2 nF ~ 20 mF



- Transistor Test, Continuity Test & Diode Test, Auto Power Off,
- Low Batt. Indication, 9 Volt Battery Operated,
- Dimension & Weight : 175 × 93 × 55 mm, & Approx. 400 gms. (incl. Batt.)
- Accessories Supplied : Test Leads, User Manual & Battery (Installed / Kept Aside)

CAMBRIDGE INSTRUMENTS & ENGINEERING CO.

✉ [cieinstruments@gmail.com](mailto:cieinstruments@gmail.com)